

Due Mon Feb 11 at the beginning of class.

1. For each of the ASM instructions below, identify the address mode.
  - a. LDAA \$E3
  - c. EORB #\$69
  - d. STX \$1A,Y
  - b. CPD #255
  - e. DEC \$6011
  
2. For each of the ASM instructions in Problem 1, briefly explain their operation in your own words. Be specific regarding data values and memory locations.
  
3. For each of the ASM instructions in Problem 1, use the Instruction Charts at the end of this homework to show the contents of CPU registers and Memory after each instruction is executed. Assume the Initial Values shown at the top of the page are used for each instruction. You only need to show values that change, including CCR bits (except H which is not on the chart).
  
4. Consider the instruction: LDAB \$E6
  - a. What does this instruction accomplish?
  - b. What address mode does this instruction use?
  - c. What machine code bytes will be stored in program memory to represent this instruction?
  - d. Describe each step in sequence of the instruction execution cycle for this instruction.
  
5. Address mode examples. Write complete instructions, with operands when necessary.
  - a. Write an example instruction that uses *inherent* address mode.
  - b. Using *immediate* address mode, write an instruction to load the value \$101 into accumulator D.
  - c. Using *extended* address modes, write an instruction to store the contents of the accumulator B into memory at \$806B
  - d. Using *direct* address mode, write an instruction to store the contents in accumulator X into memory at \$00B0 & \$00B1
  - e. Using *indexed* address mode with \$6A00 in index X, store the value in accumulator A to memory at location \$6AA6.
  
6. Write a complete ASM instruction to implement each of the following operations:
  - a. Load accumulator B with the 8-bit value located in memory address \$4500.
  - b. AND the contents of accumulator\_B with the value \$2B.
  - c. Add the contents of accumulator\_B to the contents of index\_register\_X.
  - d. Compare the contents in index\_register\_Y to the value stored at \$2112 and \$2113.
  - e. Copy the contents of the CCR to accumulator\_B.
  - f. Increment the contents in accumulator\_A by 1.
  
7. Indexed Addressing: Describe the results for each of the following ASM instructions when performed in sequence. Specify all relevant (modified) register and memory values in hexadecimal.
 

```
LDAA  #$10
LDY   #$01FB
STAA  11,Y
```

*As described in the PC Lab 1 slides, you can access an ASM simulator in several ways including DECS labs, programs off the internet (see class website for links), or the software in the back of your textbook. Please ensure that you have good access to an ASM simulation program because you will be writing/simulation several programs for homework in this course.*

8. At the end of this homework, attach a printout of your final Example 2 program from PC Lab 1. Include answers to the questions at the bottom of page 9 in PC Lab 1 slides.

Instruction Charts for Problem 3

Action: **Initial Values** A

aA	<b>\$AA</b>	aB	<b>\$BB</b>	\$00E2	<b>\$A0</b>
IX	<b>\$01F0</b>			\$00E3	<b>\$00</b>
IY	<b>\$6010</b>			\$6010	<b>\$04</b>
SP	ignore			\$6011	<b>\$B2</b>
PC	ignore			\$601A	<b>\$C1</b>
CCR	N	Z	V	C	\$602A
				\$602B	<b>\$77</b>
				address	value

Initial Values

Action: \_\_\_\_\_ B

aA		aB		\$00E2	
IX				\$00E3	
IY				\$6010	
SP	ignore			\$6011	
PC	ignore			\$601A	
CCR	N	Z	V	C	\$602A
				\$602B	
				address	value

(a)

Action: \_\_\_\_\_ B

aA		aB		\$00E2	
IX				\$00E3	
IY				\$6010	
SP	ignore			\$6011	
PC	ignore			\$601A	
CCR	N	Z	V	C	\$602A
				\$602B	
				address	value

(b)

Action: \_\_\_\_\_ B

aA		aB		\$00E2	
IX				\$00E3	
IY				\$6010	
SP	ignore			\$6011	
PC	ignore			\$601A	
CCR	N	Z	V	C	\$602A
				\$602B	
				address	value

(c)

Action: \_\_\_\_\_ B

aA		aB		\$00E2	
IX				\$00E3	
IY				\$6010	
SP	ignore			\$6011	
PC	ignore			\$601A	
CCR	N	Z	V	C	\$602A
				\$602B	
				address	value

(d)

Action: \_\_\_\_\_ B

aA		aB		\$00E2	
IX				\$00E3	
IY				\$6010	
SP	ignore			\$6011	
PC	ignore			\$601A	
CCR	N	Z	V	C	\$602A
				\$602B	
				address	value

(e)